

Cambridge Assessment International Education

Cambridge International General Certificate of Secondary Education

COMPUTER SCIENCE

Paper 2

MARK SCHEME

Maximum Mark: 50

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.

Cambridge International is publishing the mark schemes for the May/June 2018 series for most Cambridge IGCSE™, Cambridge International A and AS Level and Cambridge Pre-U components, and some Cambridge O Level components.

 $\mathsf{IGCSE}^{\intercal} \mathsf{m} \text{ is a registered trademark}.$

This syllabus is approved for use in England, Wales and Northern Ireland as a Cambridge International Level 1/Level 2 Certificate.



Generic Marking Principles

These general marking principles must be applied by all examiners when marking candidate answers. They should be applied alongside the specific content of the mark scheme or generic level descriptors for a question. Each question paper and mark scheme will also comply with these marking principles.

GENERIC MARKING PRINCIPLE 1:

Marks must be awarded in line with:

- the specific content of the mark scheme or the generic level descriptors for the question
- the specific skills defined in the mark scheme or in the generic level descriptors for the question
- the standard of response required by a candidate as exemplified by the standardisation scripts.

GENERIC MARKING PRINCIPLE 2:

Marks awarded are always whole marks (not half marks, or other fractions).

GENERIC MARKING PRINCIPLE 3:

Marks must be awarded **positively**:

- marks are awarded for correct/valid answers, as defined in the mark scheme. However, credit is given for valid answers which go beyond the scope of the syllabus and mark scheme, referring to your Team Leader as appropriate
- marks are awarded when candidates clearly demonstrate what they know and can do
- · marks are not deducted for errors
- · marks are not deducted for omissions
- answers should only be judged on the quality of spelling, punctuation and grammar when these features are specifically assessed by the question as indicated by the mark scheme. The meaning, however, should be unambiguous.

GENERIC MARKING PRINCIPLE 4:

Rules must be applied consistently e.g. in situations where candidates have not followed instructions or in the application of generic level descriptors.

© UCLES 2018 Page 2 of 11

GENERIC MARKING PRINCIPLE 5:

Marks should be awarded using the full range of marks defined in the mark scheme for the question (however; the use of the full mark range may be limited according to the quality of the candidate responses seen).

GENERIC MARKING PRINCIPLE 6:

Marks awarded are based solely on the requirements as defined in the mark scheme. Marks should not be awarded with grade thresholds or grade descriptors in mind.

© UCLES 2018 Page 3 of 11

Question	Answer					
		Section A				
1(a)(i)	Many correct answers, the	y must be meaningful. The following is an example only:	4			
	One mark per bullet point					
	Data structureNameData typeUse	Array processor string to store processors currently available				
1(a)(ii)	Many correct answers, the	ey must be meaningful. The following is an example only:	4			
1(b)	One mark for method, one Many correct answers, an		2			
	Use a previously stored nu Update it (by 1) every time	umber//generates/uses an initial value (1) an estimate is made (1)				

© UCLES 2018 Page 4 of 11

Question	Answer	Marks
1(c)	Any five from: Initialise (stock level) flag Check stock level for the chosen processor type Only check RAM if processor available // Only check processor if RAM available Check stock level for the chosen type of RAM Finish process if problem with (RAM/Processor) stock levels Identify out of stock (processor/RAM)//Set flag to appropriate value Identify stock level OK//Set flag to appropriate value	5

© UCLES 2018 Page 5 of 11

Question	Answer	Marks
1(c)	Sample answer:	
	foundProc ← FALSE	
	count ← 1	
	WHILE NOT foundProc AND count <= 3 DO	
	<pre>IF processor(estNo) = proc(count) AND stProc(count) > 0 THEN</pre>	
	foundProc ← TRUE ENDIF	
	count ← count + 1	
	ENDWHILE	
	IF foundProc	
	THEN	
	foundRAM ← FALSE	
	IF RAM(estNO) = RAM1 AND stRAM1 >0	
	THEN	
	foundRAM ← TRUE	
	stRAM1 ← stRAM1 - 1	
	ENDIF	
	IF RAM(estNO) = RAM2 AND stRAM2 >0	
	THEN	
	foundRAM ← TRUE	
	stRAM2 ← stRAM2 - 1	
	ENDIF	
	ENDIF	
	IF NOT foundProc	
	THEN	
	OUTPUT "Processor out of stock"	
	ELSE	
	$stProc(count) \leftarrow stProc(count) - 1$ $ENDIF$	
	IF NOT foundRAM	
	THEN	
	OUTPUT "RAM out of stock"	
	ENDIF	

© UCLES 2018 Page 6 of 11

Question	Answer	Marks
1(d)	One mark for each correct point (max 5):	5
	Explanation How the number of orders was calculated Deal with the case where the estimate has not been turned into an order Calculating the total number of each component sold Details of method actually used to calculate numbers of components How the total value of all the orders was calculated Display summary Display complete summary of number of orders, total number of components and total value of orders Programming statements can be used but must be explained to gain credit.	

© UCLES 2018 Page 7 of 11

Question	Answer	Marks
	Section B	
2(a)	Any six from: 1 Initialisation of counters for positive numbers and zeros 2 Appropriate loop for 1000 iterations 3 Input number inside loop 4 Test for positive numbers 5 Update positive number counter 6 Test for zeros 7 Update zero counter 8 Output counters with appropriate messages outside loop	6
	<pre>zero ← 0 posCount ← 0 FOR count ← 1 TO 1000 INPUT number IF number > 0 THEN posCount ← posCount + 1 ENDIF IF number = 0 THEN zero ← zero + 1 ENDIF NEXT OUTPUT posCount, " positive numbers" OUTPUT zero, " zeros"</pre>	
2(b)	Reduce the number of iterations to a manageable amount // Simulate the input (e.g. random generation)	1

© UCLES 2018 Page 8 of 11

Question		Answer							Marks			
3(a)	Digit	1) Dig	it(2)	Digit(3)	Digit(4)	Digit(5)	Digit(6)	Digit(7)	Digit(8)	Sum	OUTPUT	
	5	7	7	0	1	2	3	4	6	44	GTIN-8	
											57012346	
	Digit	1) Dig	it(2)	Digit(3)	Digit(4)	Digit(5)	Digit(6)	Digit(7)	Digit(8)	Sum	ОИТРИТ	
	4	(3	1	0	2	3	1	0	30	GTIN-8	
											43102310	
3(b)	Any three from 1 Change first loop to 8 iterations 2 Check that the input Digit (8) is equal to the calculated Digit (8) 3 if equal output check digit correct											
	Or											
	 1 Change first loop to 8 iterations 2 Put all 8 digits through the algorithm to calculate Sum 3 if MOD (Sum, 10) is equal to zero, check digit correct 4 otherwise output check digit incorrect 											

© UCLES 2018 Page 9 of 11

Question	Answer	Marks
4	One mark for each (max three) 10.00 boundary/erroneous data // the price should be rejected // value is out of range 9.99 boundary/extreme/normal data // the prices should be accepted // value is within normal range erroneous/abnormal data // input should be rejected // value is wrong type	3

Question	Answer	Marks
5	There are many possible answers. e.g.:	4
	Totalling is used to sum a list of numbers (1) Counting is used to find how many numbers/items there are in a list. (1) Totalling example (1) e.g. Total = Total + Number Counting example (1) e.g. Counter = Counter + 1	

Question	Answer	Marks
6(a)	Fields 5 Records 8	2
6(b)	Any two from: Length check Type check Presence check Format check	2

© UCLES 2018 Page 10 of 11

Question	Answer							
6(c)	Field:	Туре	Sold Out	Date	Title	4		
	Table:	PERFORMANCE	PERFORMANCE	PERFORMANCE	PERFORMANCE			
	Sort:							
	Show:			\square	Ø			
	Criteria:	Like "Jazz"	False					
	or:							
	One mark po	er correct column.	·					

© UCLES 2018 Page 11 of 11